



QOLTEC PURE SINE WAVE INVERTER MONOLITH | BATTERY CHARGER | UPS | 1000W | 2000W | 12V TO 230V | LCD

PRICE: -,-- EUR

SHIPPING TIME: 24 HOURS

CATALOG NUMBER: 51942

EAN CODE: 5901878519425

PRODUCENT: QOLTEC

MOC ZNAMIONOWA: 1000W

MOC CAŁKOWITA (CHWILOWA): 2000W (5 SEKUND)

NAPIĘCIE WEJŚCIOWE: 12V

NAPIĘCIE WYJŚCIOWE: 230V ± 5%

PRZEBIEG NAPIĘCIA NA WYJŚCIU: CZYSTA FALA
SINUSOIDALNA

CZĘSTOTLIWOŚĆ WYJŚCIOWA: 50HZ ± 0.5 HZ

ZNIEKSZTAŁCENIA FALI: THD<3%

ŁADOWANIE STAŁYM NAPIĘCIEM: 14.6VDC

ZAKRES NAPIĘCIA WEJŚCIOWEGO: 190 ~260VAC

ŁADOWANIE STAŁYM PRĄDEM: 15A

ŁADOWANIE BUFOROWE: 13.8VDC

PRĄD WEJŚCIOWY: 10A

PRĄD WYJŚCIOWY: 15A

PRĄD JAŁOWY: >0.8A

SPRAWNOŚĆ: 90%

CHŁODZENIE: INTELIGENTNE CHŁODZENIE

PORTY USB: 5V/1A

ZABEZPIECZENIA: LVP/OVP/OC/OTP/SCP

ZABEZPIECZENIE PRZED ODWROTĄ POLARYZACJĄ: TAK

MATERIAŁ: ALUMINIUM

TEMPERATURA PRACY: -10°C ~ +50°C

TEMPERATURA PRZECHOWYWANIA: -30°C ~ +70°C

INFORMACJE DODATKOWE: NIE ZAKRYWAJ OTWORÓW
WENTYLACYJNYCH URZĄDZENIA PAMIĘTAJ O
PRAWIDŁOWYM PODŁĄCZENIU PRZEWODÓW I
POLARYZACJI NAPIĘCIA ZASILAJĄCEGO ! FUNKCJA
MIĘKKIEGO STARTU

WYMIARY (G/D X SZ X W): 180 X 400 X 70 MM

ZAWARTOŚĆ ZESTAWU: 1 X PRZETWORNICZKA 4 X

BEZPIECZNIK 1 X ZESTAW PRZEWODÓW 1 X KLUCZ DO
MONTAŻU PRZEWODÓW 1 X KARTA GWARANCYJNA 1 X

INSTRUKCJA OBSŁUGI

GŁĘBOKOŚĆ / DŁUGOŚĆ OPAKOWANIA [MM]: 225

SZEROKOŚĆ OPAKOWANIA [MM]: 445

WYSOKOŚĆ OPAKOWANIA [MM]: 95

WAGA NETTO [KG]: 3.700

WAGA BRUTTO [KG]: 4.400

CERTYFIKAT: CE

GWARANCJA: 24 MIESIĄCE

ZASTOSOWANIE: SPRZĘT KUCHENNY : LODÓWKA, KUCHENKA MIKROFALOWA, BLENDER, EKSPRES DO KAWY, CZAJNIK, ZAMRAŻARKA, PIEKARNIK SPRZĘT BIUROWY: LAPTOP, KOMPUTER, DRUKARKA INNE: ELEKTRONARZĘDZIA, ODKURZACZ, SUSZARKA, WENTYLATOR, TV, KONSOLA DO GIER, RADIO, SPRZĘT MUZYCZNY, PANE

ITEM DESCRIPTION

THREE FUNCTIONS IN ONE DEVICE



QOLTEC BRAND INVERTER IS A COMBINATION OF FUNCTIONS :

- **12 VOLT TO 230 VOLT INVERTER**, WHEN CONNECTED TO THE BATTERY, THE INVERTER DRAWS THE NECESSARY ENERGY TO POWER THE CONNECTED DEVICE,
- **BATTERY CHARGER**, WHEN CONNECTED TO THE MAINS, THE DEVICE AUTOMATICALLY ENTERS BATTERY CHARGING MODE,
- **UPS**, WHEN A POWER OUTAGE FROM THE MAINS IS DETECTED, THE DEVICE GOES INTO EMERGENCY POWER MODE, USING THE ENERGY STORED IN THE BATTERY UNTIL THE MAINS VOLTAGE IS RESTORED.

THE INVERTER CAN SIMULTANEOUSLY CHARGE THE BATTERY AND POWER THE CONNECTED DEVICES.

VOLTAGE CONVERTER OR MOBILE ENERGY IN A PURE WAY



QOLTEC BRAND INVERTER IS A **PURE SINE WAVE** , PRODUCES THE SAME CURRENT AS A 230V SOCKET , ENSURING SAFETY FOR ALL CONNECTED DEVICES . GREAT FOR BOTH DURING POWER OUTAGES , AS WELL AS DURING TRAVEL WHEN WE DO NOT HAVE ACCESS TO AN OUTLET . WHEN CHOOSING A SUITABLE INVERTER, **IT IS WORTH PAYING ATTENTION TO THE VOLTAGE OF THE BATTERY**, WHICH MUST BE CONSISTENT WITH THAT INDICATED ON THE INVERTER TO ENSURE THAT OUR EQUIPMENT HAS THE RIGHT CONDITIONS FOR WORK. ALSO **IMPORTANT IS THE NUMBER OF CONNECTED DEVICES**, FOR EXAMPLE, CONNECTING A LAPTOP AND A PRINTER, THE POWER OF BOTH DEVICES SHOULD BE ADDED UP. REMEMBER THAT **THE POWER CONSUMED BY THE CONNECTED DEVICE SHOULD NOT EXCEED 85% OF THE RATED POWER OF THE INVERTER**.

DON'T LOSE ENERGY ON THE JOURNEY



THE PRODUCT WILL BE IDEAL AS A POWER SOURCE IN CAMPERS OR TRAILERS DURING FAMILY TRIPS. WITH THE INVERTER, YOU WILL BE ABLE TO POWER YOUR DEVICES ANYWHERE AND ENJOY CONVENIENCE AND COMFORT. DEPENDING ON THE POWER CONSUMED BY THE DEVICE, **THE 1000W INVERTER CAN POWER SUCH DEVICES AS :**

- RTV EQUIPMENT : TV, GAME CONSOLE, MUSIC EQUIPMENT, RADIO,
- HOUSEHOLD APPLIANCES : REFRIGERATOR, MICROWAVE, FREEZER,
- OFFICE EQUIPMENT : COMPUTERS, PRINTERS, LAPTOPS,
- OTHER : POWER TOOLS.



THE INVERTER CAN ALSO BE USED NOT ONLY ON THE GO, BUT ALSO AS **AN EMERGENCY POWER SOURCE, SUCH AS BACKING UP THE CO FURNACE OR TO POWER EQUIPMENT AS A UPS DURING A TEMPORARY POWER OUTAGE FROM THE POWER GRID.**



DURABLE AND LIGHTWEIGHT HOUSING



THE CASE IS DESIGNED FROM **HIGH QUALITY ALUMINUM** THAT IS RESISTANT TO **SHOCK AND MECHANICAL DAMAGE**. IT IS AN IDEAL CHOICE FOR THOSE WHO LIKE TO TRAVEL FOR LONG PERIODS OF TIME. THANKS TO THE INVERTER WITH BUILT-IN POWER SOCKET, YOU CAN USE ALMOST ANY DEVICE THAT REQUIRES CONNECTION TO THE SOCKET. EQUIPPED WITH AN **LCD DISPLAY** , WHICH MONITORS ALL THE MOST IMPORTANT PARAMETERS OF THE DEVICE. THE PRODUCT HAS A **USB PORT** FOR CHARGING MOBILE DEVICES AND A **FAN** THAT TAKES CARE OF PROPER COOLING .

MULTIFUNCTIONAL LCD DISPLAY



THE INVERTER IS EQUIPPED WITH AN LCD DISPLAY, WHICH INFORMS US ABOUT THE CURRENT BATTERY LEVEL, THE POWER OF THE CONNECTED DEVICES, AND THE AC AND DC VOLTAGE. YOU CAN MONITOR THE OPERATING PARAMETERS OF THE DEVICE, MAKING IT EASY, SAFE AND RELIABLE TO WORK WITH THE INVERTER.

FULL GUARANTEE FOR SAFE USE



THE PRODUCT IS EQUIPPED WITH A NUMBER OF PROTECTIONS THAT GUARANTEE FULL PROTECTION FOR CONNECTED DEVICES. IN ADDITION, THE KIT INCLUDES A **SPARE FUSE** TO ENSURE THE LONGEST POSSIBLE OPERATION OF THE EQUIPMENT.

THE CONVERTER HAS :

UVP PROTECTION - PROTECTS DEVICES FROM TOO LOW VOLTAGE AT THE OUTPUT, WHICH AFFECTS THE STABILITY OF CONNECTED DEVICES,

SCP PROTECTION - IS A SHORT CIRCUIT PROTECTION,

OVP PROTECTION - IS PROTECTION AGAINST TOO HIGH OUTPUT VOLTAGE AND DAMAGE TO CONNECTED DEVICES,

OCP PROTECTION - IS PROTECTION AGAINST TOO HIGH CURRENT ON THE LINE,

OTP PROTECTION - IS PROTECTION AGAINST OVERHEATING.

CONFIDENCE CONFIRMED BY A WARRANTY

DO YOU CARE ABOUT THE HIGH QUALITY OF THE PRODUCT YOU BUY? OUR SOLUTIONS WILL MEET YOUR EXPECTATIONS. THE PRODUCT COMES WITH A **24-MONTH WARRANTY** VALID FROM THE DATE OF PURCHASE.