



QOLTEC PORTABLE POWER BANK MONOLITH | 350W | 300WH | 2XUSB | LCD

PRICE: -,-- EUR

SHIPPING TIME: 24 HOURS

CATALOG NUMBER: 50179

EAN CODE: 5901878501796

PRODUCENT: QOLTEC

WEJŚCIE DC: 16-24V | 1-5A | 5.5X2.1 PANEL SOLARNY

WYJŚCIE AC: 220V ± 10%

MOC WYJŚCIOWA: 350W

SZCZYTOWA MOC WYJŚCIOWA: 700W

ZABEZPIECZENIE PRZED PRZEKROCZENIEM

MAKSYMALNEJ MOCY: 400W

KSZTAŁT FALI: CZYSTA FALA SINUSOIDALNA

CZĘSTOTLIWOŚĆ WYJŚCIOWA: 50~60 HZ

WBUDOWANA BATERIA: AKUMULATOR LITOWO-JONOWY
18650 (OGNIWO CYLINDRYCZNE)

POJEMNOŚĆ BATERII: 2600MAH/3.7V CAŁKOWITA

POJEMNOŚĆ 124800MAH ZASILANIE BATERYJNE :
27AH/11.1V (300WH)

ILOŚĆ CYKLI ŁADOWANIA: POWYŻEJ 1000

CZAS ŁADOWANIA: 8-10 GODZIN OD 0%-100% Z
AUTOMATYCZNYM WYŁĄCZENIEM

ZASILACZ: 20V/5A | ZASILACZ Z WTYCZKĄ 5.5X2.1

WYŚWIETLACZ: LCD

USB: 2 X USB QC 3.0 , 5V/3A, 9V/2A, 12V/1.5A | MAX
18W USB TYP C (PD 5V/3A, 9V/2A, 12V/1.5A | MAX 18W)
USB TYP C (PD 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/3A|
MAX 60W)

WYJŚCIE DC: 2 X WTYCZKA 5.5 X 2.1 (12V/13A) 1 X
GNIAZDO ZAPALNICZKI (12V/13A -150W MAX)

WSPOMAGANIE ROZRUCHU: BRAK

POBÓR PRĄDU: <10W

ŹRÓDŁO ŚWIATŁA: LATARKA LED

CHŁODZENIE: 2 X WENTYLATOR

GŁOŚNOŚĆ: DO 60 DB (W ZALEŻNOŚCI OD OBCIĄŻENIA)

ZABEZPIECZENIA: - PRZECIWZWARCIOWE -

NADNAPIĘCIOWE - NADPRĄDOWE - PRZECIW

PRZECIĄŻENIOWE - PRZED NISKIM NAPIĘCIEM -

OCHRONA PRZED PRZEGRZANIEM : ≥ 85°C

ZASTOSOWANIE: SPRZĘT RTV : TV, LAPTOP, PROJEKTOR,
TELEFON, SPRZĘT AGD : LODÓWKA TURYSTYCZNA,
SOKOWIRÓWKA ELEKTRONARZĘDZIA ROWER
ELEKTRYCZNY GRZEJNIK ELEKTRYCZNY DRON
OŚWIETLENIE LED

TEMPERATURA PRACY: 0°C ~ +40°C

TEMPERATURA PRZECHOWYWANIA: -10°C ~ +40°C

INFORMACJE DODATKOWE: BMS

UWAGI: PROSIMY O UWAŻNE PRZECZYTANIE INSTRUKCJI
OBSŁUGI PRZED ROZPOCZĘCIEM PRACY Z URZĄDZENIEM
JEŻELI URZĄDZENIE NIE BĘDZIE UŻYWANE PRZEZ
DŁUŻSZY CZAS , WBUDOWANA BATERIA ROZŁADUJE SIĘ.
ZALECAMY ABY ŁADOWAĆ BATERIĘ CO 6 MIESIĘCY.

WYMIARY (G/D X SZ X W): 163 X 240 X 176 MM

ZAWARTOŚĆ OPAKOWANIA: 1 X BANK ENERGII 1 X

ZASILACZ 1X INSTRUKCJA OBSŁUGI 1 X KARTA

GWARANCYJNA

GŁĘBOKOŚĆ / DŁUGOŚĆ OPAKOWANIA [MM]: 215

SZEROKOŚĆ OPAKOWANIA [MM]: 295

WYSOKOŚĆ OPAKOWANIA [MM]: 240

WAGA NETTO [KG]: 4.300

WAGA BRUTTO [KG]: 4.700

CERTYFIKAT: CE

GWARANCJA: 24 MIESIĄCE

ITEM DESCRIPTION

YOUR MOBILE POWER BANK



THE MONOLITH PORTABLE POWER BANK WILL **PROVIDE YOU WITH RELIABLE POWER ANYWHERE, ANYTIME**. THIS PORTABLE POWER SOURCE IS THE ANSWER TO THE GROWING NEED FOR EXTERNAL POWER. THE STATION, THANKS TO ITS SMALL SIZE AND LARGE NUMBER OF CHARGING PORTS, **WILL PROVE USEFUL ON ANY FAMILY TRIP, AT A CAMPGROUND, IN AN RV, ON A BOAT**, BUT ALSO AS **AN EMERGENCY POWER SOURCE** AT HOME DURING POWER BREAKS.

A PRODUCT WORTH YOUR ATTENTION



THE POWER STATION WILL EASILY **CHARGE MOST DEVICES** AVAILABLE ON THE MARKET SUCH AS : SMARTPHONE, TABLET, LAPTOP, DIGITAL CAMERA, WIRELESS HEADPHONES. DESPITE ITS SMALL SIZE, IT HAS A BUILT-IN UPS FUNCTION. IN ADDITION, THE STATION IS DISTINGUISHED BY :

- EASY OPERATION OF THE DEVICE,
- BUILT-IN INVERTER RESPONSIBLE FOR CHANGING DIRECT CURRENT TO ALTERNATING CURRENT,
- FAST CHARGING OF THE DEVICE THE STATION IS EQUIPPED WITH USB PORTS WITH **POWER DELIVERY FUNCTION**,
- PORTABLE POWER BANK **CAN BE USED AS A UPS AS AN EMERGENCY POWER SOURCE** WHEN WE DON'T HAVE ACCESS TO THE MAINS,
- **FLASHLIGHT FUNCTION** WITH SOS MODE,
- EQUIPPED WITH **LCD DISPLAY**, SHOWING DEVICE OPERATION, CHARGING PROGRESS, BATTERY LEVEL, INVERTER STATUS AND AVAILABLE TIME,
- **PURE SINE WAVE**,
- HAS **2 USB QC SOCKETS, 2 USB TYPE C SOCKETS WITH POWER DELIVERY** FUNCTION WITH MAXIMUM POWER OF 18W AND 60W, AND **2 DC CIGARETTE LIGHTER SOCKETS** WITH MAXIMUM POWER OF 150W, CAR START OUTPUT WITH MAXIMUM POWER,
- LIGHTWEIGHT AND HANDY, IT HAS A **CONVENIENT HANDLE TO CARRY THE DEVICE**,
- THE STATION CAN **CHARGE AND POWER ANOTHER DEVICE AT THE SAME TIME**.
- POSSIBILITY TO CONNECT A **SOLAR PANEL**.

THREE CHARGING OPTIONS



THE PRODUCT HAS SEVERAL INPUT PORTS, MAKING IT POSSIBLE TO CHARGE THE STATION USING DIFFERENT ENERGY SOURCES.

THE STATION HAS **3 OPTIONS** FOR CHARGING BATTERIES :

- CHARGING DIRECTLY FROM THE **230V AC MAINS**, THROUGH THE INCLUDED POWER SUPPLY - ALLOWS YOU TO ACCUMULATE A LARGER SUPPLY OF ENERGY,
- CHARGING FROM A **DC POWER SOURCE**, A PARTICULARLY HELPFUL OPTION WHEN DRIVING A CAR, WHEN WE ARE ON THE ROAD AND WANT TO SAVE TIME,
- POSSIBLE CONNECTION TO A **SOLAR PANEL**, JUST CONNECT THE STATION AND USE SOLAR ENERGY.



YOU CAN CONNECT A **SOLAR PANEL AND GAIN UNLIMITED ACCESS TO CLEAN SOLAR ENERGY**. IN ORDER TO ACCUMULATE AS MUCH ENERGY AS POSSIBLE, ALL YOU NEED TO DO IS TO PLACE THE PANELS IN A POSITION WITH ADEQUATE SUNLIGHT. IN TURN, WHEN BUYING A SOLAR PANEL, WE RECOMMEND TAKING INTO ACCOUNT ITS POWER. REMEMBER THAT THE HIGHER THE POWER, THE FASTER IT WILL CHARGE THE POWER STATION.



THE PRODUCT IS EQUIPPED WITH A NUMBER OF PROTECTIONS THAT GUARANTEE FULL PROTECTION FOR CONNECTED DEVICES. THE CONVERTER HAS :

YOU CARE ABOUT THE QUALITY OF THE PRODUCT YOU BUY, SO OUR DESIGNS AND SOLUTIONS ARE GEARED TO MEET

YOUR EXPECTATIONS. EACH BATTERY WE OFFER IS GUARANTEED FOR **24 MONTHS** FROM THE DATE OF PURCHASE.